

Solid State Amplifiers

> **compact family PJC-LCD series**

PJ502C-LCD PJ702C-LCD



PJ702C-LCD front view

Features

- > **PRIMARY APPLICATION:** uncompromised amplification power at a very attractive price. Ideal for small to medium power stations.
- > **AMPLIFIER FEATURES:** high-gain amplifier with very low input drive power requirement and adjustable power output from 10 to 100 %.
- > **HARDWARE FEATURES:** extremely compact and rugged thanks to the stainless steel chassis, in only 2HE.
- > **USER-FRIENDLY FEATURES:** universal 80-260 V multi-voltage power supply enables operation without preselect voltage. Four pushbuttons for user/device interaction and software that offers a simple, intuitive interface..
- > **OPERATING EFFICIENCY:** incorporate a PFC (Power Factor Corrector) power supply, that provides the utmost efficiency for enhanced energy saving and environmental protection, which added to LD-MOSFET technology ensure high efficiency, better than 70% across the bandwidth.
- > **EASE OF MAINTENANCE:** advanced module engineering ensures extreme ease of access and simple maintenance.
- > **RELIABILITY/CONTINUITY:** APC (Automatic Power Control) and Foldback protection ensure reliable operation under any operating conditions.
- > **INTERFACE CONTROL:** total control thanks to microprocessor easily programmed from menu with all key parameters displayed on LCD.
- > **REMOTE CONTROL:** electromechanically controllable and integrable into all digital **RVR** telemetry systems.
- > **REGULATORY COMPLIANCE:** state-of-the-art technology in full compliance with EC, FCC and CCIR standards.

Caratteristiche

- > **PRIMARY APPLICATION:** potenza di amplificazione senza compromessi ad un prezzo estremamente contenuto. Ideale come complemento per stazioni di piccola e media potenza.
- > **AMPLIFIER FEATURES:** amplificatore ad alto guadagno con potenza di pilotaggio in ingresso estremamente basso e potenza di uscita regolabile dal 10 al 100%.
- > **HARDWARE FEATURES:** estremamente compatto e indeformabile perchè realizzato in chassis di acciaio inox, in sole 2 unità rack.
- > **USER-FRIENDLY FEATURES:** utilizzabile a diverse tensioni di rete da 80 V a 260 V senza necessità di preselezione. Quattro tasti a pressione per l'interazione fra l'utente e l'apparato unita ad un software intuitivo e semplificato.
- > **OPERATING EFFICIENCY:** per un risparmio di risorse energetiche e ambientali, utilizzano un alimentatore PFC (Power Factor Corrector) che sommato alla tecnologia LD-MOSFET garantisce rendimenti elevati, superiori al 70% su tutta la banda.
- > **EASE OF MAINTENANCE:** estrema accessibilità e semplicità di manutenzione grazie ad una avanzata ingegnerizzazione modulare dell'apparato.
- > **RELIABILITY/CONTINUITY:** elevata continuità di esercizio garantita in qualsiasi condizione di lavoro attraverso un controllo automatico APC ed una protezione di Foldback.
- > **INTERFACE CONTROL:** controllo completo basato su microprocessore e da menu con lettura su display LCD di tutti i parametri principali.
- > **REMOTE CONTROL:** elettromeccanicamente controllabile ed integrabile in tutti i sistemi di telemetria digitali **RVR**.
- > **REGULATORY COMPLIANCE:** tecnologia moderna e pienamente rispondente alle normative EC, FCC ed CCIR.



Solid State Amplifiers

(Oirt, JPN &
China Band
others
on request)

Technical specifications

Parameter		PJ502C-LCD		PJ702C-LCD
		Value		
GENERALS				
Frequency range		FCC - CCIR - OIRT - JPN – CHN		
Rated output power		500 W	700 W	
Driver power for rated output		15 W		
Max input power before protection		20 W		
Environmental working conditions		-10 °C to + 50 °C / 95% relative Humidity non condensing		
POWER REQUIREMENTS				
AC Power Input	AC Supply Voltage	230 VAC ±15%		
	Active Power Consumption	714 W	1000 W	
	Overall Efficiency	Typical 70 %		
	Connector	VDE IEC Standard		
MECHANICAL DIMENSIONS				
Physical Dimensions	L x H x W	483 mm x 88 mm x 390 mm		
Weight		about 10 kg		
Cooling		Forced, with internal fan		
Acoustic Noise		< 75 dBA		
INPUTS				
RF Input		50 Ohm (N type)		
OUTPUTS				
RF Output		50 Ohm (N type)		
RF Monitor		50 Ohm (BNC) approx. -60 dBc		
FUSES				
On Mains		1 External fuse F 16 – 5x20 mm		

All pictures are RVR's property and they are only indicative and not binding. The pictures can be modified without notice.
These are general specifications. They show typical values and are subject to change without notice.

CE 99/5/CE Revision: 06/13

Ordering Information

Code -Codice	Description - Descrizione
Options for PJC-LCD – Opzioni per PJC-LCD	
/CNT7/16-175	7/16" output RF connector. Connettore RF di uscita 7/16".

solid state
amplifiers